

#### 2900414

https://www.phoenixcontact.com/pc/products/2900414

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Hybrid motor starter for reversing  $3\sim$  AC motors up to 500 V AC and 2.4 A output current, with 24 V DC control voltage, adjustable overload shutdown and emergency stop function to SIL 3 / PL e and screw connection

### Your advantages

- 22.5 mm wide
- Safety level in accordance with IEC 61508-1: SIL 3, ISO 13849: PL e
- · Reduction in wiring
- · Long service life
- · Space saving
- 3-phase loop bridges
- · Adjustable current for bimetal function
- · Low-wear switching

#### Commercial data

Item number	2900414
Packing unit	1 pc
Minimum order quantity	1 pc
Product key	CK7412
Catalog page	Page 28 (C-5-2019)
GTIN	4046356504058
Weight per piece (including packing)	323.1 g
Weight per piece (excluding packing)	269.6 g
Customs tariff number	85371098
Country of origin	DE



2900414

https://www.phoenixcontact.com/pc/products/2900414

## Technical data

#### **Product properties**

Product type	Hybrid motor starters
Product family	CONTACTRON
Operating mode	100% operating factor

#### **Electrical properties**

Number of phases	3
Motor starter type	Reversing starter
Switching frequency	≤ 2 Hz (Load-dependent)
Maximum power dissipation for nominal condition	2.2 W
Switching frequency	≤ 2 Hz (Load-dependent)
Maximum power dissipation	3.3 W
Minimum power dissipation	1.1 W
Coordination type	1
C. malu	
Supply	211/122
Rated control circuit supply voltage U <sub>S</sub>	24 V DC
Control supply voltage range	19.2 V DC 30 V DC
Rated control supply current $I_S$	40 mA
Protective circuit	Surge protection
	Reverse polarity protection
Insulation characteristics	
Rated insulation voltage	500 V
Rated surge voltage	6 kV
Overvoltage category	III
Degree of pollution	2
Insulation characteristics between the control input and control supply voltage, and auxiliary circuit to the main circuit	Safe isolation (IEC 60947-1) at operating voltage ≤ 300 V AC
	Basic insulation (IEC 60947-1) at operating voltage 300 V AC 500 V AC
Isolation characteristics between the control input and control supply voltage to auxiliary circuit	Safe isolation (IEC 60947-1) in the auxiliary circuit $\leq$ 300 V AC

#### Input data

Control	
Input name	Control input right/left
Rated actuating voltage U <sub>C</sub>	24 V DC
Triggering voltage range	19.2 V DC 30 V DC
Rated actuating current $I_C$	5 mA (Input type 1)
Switching threshold	9.6 V ("0" signal)
	19.2 V ("1" signal)
Switching level	< 5 V DC (For EMERGENCY STOP)



#### 2900414

https://www.phoenixcontact.com/pc/products/2900414

Typical turn-off time	< 30 ms
Protective circuit	Reverse polarity protection

#### Output data

500 V AC
42 V AC 550 V AC
2.4 A (AC-51)
2.4 A (AC-53a)
50/60 Hz
180 mA 2.4 A (see to derating)
Class 10A
20 min (for auto reset)
0 mA
Surge protection

Note	Confirmation: floating change-over contact, signal contact
Contact switching type	1 changeover contact
Switching capacity in accordance with IEC 60947-5-1	3 A (230 V, AC15)
	2 A (24 V (DC13))

#### Connection data

Control circuits	
Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section rigid	0.2 mm <sup>2</sup> 2.5 mm <sup>2</sup>
Conductor cross section flexible	0.2 mm <sup>2</sup> 2.5 mm <sup>2</sup>
Conductor cross section AWG	24 14
Tightening torque	0.5 Nm 0.6 Nm
	5 lb <sub>f</sub> -in 7 lb <sub>f</sub> -in.

Load circuit

Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section rigid	0.2 mm <sup>2</sup> 2.5 mm <sup>2</sup>
Conductor cross section flexible	0.2 mm <sup>2</sup> 2.5 mm <sup>2</sup>
Conductor cross section AWG	24 14
Tightening torque	0.5 Nm 0.6 Nm
	5 lb <sub>f</sub> -in 7 lb <sub>f</sub> -in.



#### 2900414

https://www.phoenixcontact.com/pc/products/2900414

Status display	LED (yellow)
Operating voltage display	Green LED
Error indication	Red LED

#### Dimensions

Width	22.5 mm
Height	107 mm
Depth	114 mm

#### Material specifications

Flammability rating according to UL 94	V0 (Housing)
	ve (nedeling)

#### Environmental and real-life conditions

Ambient conditions	
Degree of protection	IP20
Ambient temperature (operation)	-25 °C 70 °C (observe derating)
Ambient temperature (storage/transport)	-40 °C 80 °C
Altitude	≤ 2000 m

#### Approvals

UKCA

Certificate	UKCA-compliant
ATEX	
Identification	🕼 II (2) G [Ex e] [Ex d] [Ex px]
	֎ II (2) D [Ex t] [Ex p]
Certificate	PTB 07 ATEX 3145
UL approval	
Certificate	NLDX.E228652
Safety Integrity Level (SIL, IEC 61508)	
Identification	≤ 3
Note	Safe shutdown
Safety Integrity Level (SIL, IEC 61508)	
Identification	2
Note	Motor protection
Performance Level (ISO 13849)	
Identification	≤e
Note	Safe shutdown
Category (ISO 13849)	
Identification	≤ 3



https://www.phoenixcontact.com/pc/products/2900414

UL data		
SCCR	100 kA (500 V AC (fuse: 30 A class CC/30 A class J (high fault)))	
	5 kA (500 V AC (fuse: 20 A RK5 (standard fault)))	
FLA	2.4 A (500 V AC)	
Group installation	20 A (class RK5, SCCR 5kA, #24 - 14 AWG max. solid and stranded)	
	30 A (class CC or J, SCCR 100kA, #24 - 14 AWG max, solid and stranded)	
Category code	NLDX	

#### Standards and regulations

#### Standards/regulations

Standards/regulations	IEC 60947-1
	IEC 60947-4-2
	IEC 61508
	ISO 13849

#### Mounting

Mounting type	DIN rail mounting
Assembly note	alignable, for spacing see derating
Mounting position	vertical (horizontal DIN rail, motor output below)



2900414

https://www.phoenixcontact.com/pc/products/2900414

### Drawings



#### **Conventional structure**

Main current path for reversing contactor according to category 3

K1 + K2 = Emergency stop contactor

- K3 = Left contactor
- K4 = Right contactor
- F4 = Motor protection relay



https://www.phoenixcontact.com/pc/products/2900414



Derating diagram



https://www.phoenixcontact.com/pc/products/2900414



Circuit diagram

### **Conventional structure**

Control current path reversing contactor according to category 3

- K1 + K2 = Emergency stop contactor
- K3 = Left contactor
- K4 = Right contactor
- K5 = PSR SCP-24DC.../Safety relay
- T1 = Right, T2 = Left, T3 = Reset
- S2 = Emergency stop
- F4 = Motor protection relay



https://www.phoenixcontact.com/pc/products/2900414



Circuit diagram

#### Structure with CONTACTRON

Main and control current path for '4 in 1' hybrid motor starter with reversing function according to category 3 K1 = '4 in 1' hybrid motor starter with reversing function K5 = PSR SCP-24DC.../Safety relay T1 = Right, T2 = Left, T3 = Reset S2 = Emergency stop



https://www.phoenixcontact.com/pc/products/2900414





2900414

https://www.phoenixcontact.com/pc/products/2900414

## Approvals

🌣 To download certificates, visit the product detail page: https://www.phoenixcontact.com/pc/products/2900414

	IECEE CB Scheme Approval ID: DE1-55728
EHC	EAC Approval ID: RU*C-DE.*08.B.00520*
	DNV GL Approval ID: TAA00002HK
9	UL Listed Approval ID: FILE E 323771
	CCC Approval ID: 2016010304871315
<u>.</u>	CUL Listed Approval ID: FILE E 323771
<b>.</b>	CUL Listed Approval ID: E228652
<u>©</u>	UL Listed Approval ID: E228652
<b>Æ</b> x	ATEX Approval ID: PTB 07 ATEX 3145



https://www.phoenixcontact.com/pc/products/2900414

## Classifications

#### ECLASS

ECLASS-11.0	27370905
ECLASS-12.0	27370905
ECLASS-13.0	27370905

#### ETIM

	ETIM 9.0	EC001037
UN	UNSPSC	
	UNSPSC 21.0	25173900



https://www.phoenixcontact.com/pc/products/2900414

### Environmental product compliance

#### EU RoHS

Fulfills EU RoHS substance requirements	Yes
Exemption	7(a), 7(c)-l
China RoHS	
Environment friendly use period (EFUP)	EFUP-50
	An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required.
EU REACH SVHC	
REACH candidate substance (CAS No.)	Lead(CAS: 7439-92-1)
SCIP	da3d2eb7-11ad-4a29-b238-1d9ed791a85f

Phoenix Contact 2025 © - all rights reserved https://www.phoenixcontact.com

PHOENIX CONTACT GmbH & Co. KG Flachsmarktstraße 8 D-32825 Blomberg +49 (0) 5235-3 00 info@phoenixcontact.com